



Description

The RC-1550 delivers an extraordinary level of performance. Its rock-solid power supply is comprised of a custom made toroidal transformer and select grade BHC slit foil capacitors. RC-1550 features six line-level inputs in addition to a phono input for moving magnet cartridges. A convenient contour control allows easy and repeatable timbre adjustments. With two sets of main outputs, a 12 volt "trigger" jack, and a Rotel-system remote control for both the pre-amplifier and a companion Rotel CD, tuner, or DVD player, the RC-1550 brings the flexibility and sound quality of Rotel separates within easy reach.

Specifications

THD (20-20,000Hz) 8 Ohms, all channels driven	0.006%	Tone / Contour Controls	
IM Distortion	0.006% @ 1V out	Bass	+3, +4dB at 100Hz
Input Sensitivity & Impedance		Treble	+3dB at 10kHz
Phono (MC)		Signal to Noise Ratio (IHF "A")	
Phono (MM)	1.2mV / 68kOhms	Phono (MC/MM)	70dB
Line Level Inputs	150mV / 24kOhms	Line Level	95dB
Phono Overload (MC/MM)	70mV	Power Consumption	10 watts
Output Sensitivity / Impedance	1V / 100 Ohms	Dimensions (W x H x D) mm	431 x 99 x 337 mm
Frequency Response		Dimensions (W x H x D) in	17 x 4 x 13.5 in
Phono Input	20-20kHz (+/-0.05dB)	Front Panel Height	2U (3.5")
Line Level Input	4-100kHz (+0, -3dB)	Shipping Weight	15.8 lbs.