

RC-1590MKII

STEREO PREAMPLIFIER



**ROON
TESTED**
Certified
Roon Tested

MQA
Supports MQA and
MQA Studio

**Balanced XLR
inputs and outputs**

**Moving Magnet
Phono input for
turntable connection**

**Wireless
aptX™ and AAC
Bluetooth**

**Texas Instruments
premium 32-bit/384kHz
Digital to Analog Converter**

Reference audio systems deserve reference audio equipment. The Rotel RC-1590MKII is exactly that -- a reference preamplifier rendering analog and digital sources with natural expression in a wide and open sound stage in stunning clarity.

The heart of the RC-1590MKII begins with the power supply featuring dual in-house manufacture toroidal transformers. The transformers are physically and electrically isolated supplying dedicated analog and digital supply voltages to all critical circuits through low ESR slit-foil capacitors eliminating unwanted distortion and an extremely low noise floor.

Digital source inputs are processed utilizing an audiophile grade Texas Instruments 32-bit/384kHz Digital to Audio Converter (DAC) with custom engineered, proprietary acoustically tuned external output filter circuits rendering even the finest details with exceptional clarity and exact positioning.

Analog signal paths feature DIRECT-PATH bypass modes eliminating unnecessary circuits maintaining signal integrity and further eliminating unwanted noise and distortion drawing you even closer and immersing you in the music.

The RC-1590MKII supports a full array of inputs ensuring connection to your favorite sources including a Moving Magnet Phono input for vinyl lovers, Analog, Digital, XLR Balanced, high quality aptX™ and AAC wireless Bluetooth, and PC-USB (32-bit/384kHz) supporting MQA unfolding and rendering as well as certified Roon Tested.

Dual RCA and XLR output connection provide the ultimate flexibility including bi-amplification installations. A subwoofer output is also included.

The RC-1590MKII proudly continues Rotel's 60-year legacy and heritage with our ongoing promises of performance, value, and unwavering commitment to quality. Authentic, engaging, and spacious – the RC-1590MKII proudly represents this iconic brand.

RC-1590MKII

STEREO PREAMPLIFIER



SPECIFICATIONS

Total Harmonic Distortion (20 Hz-20k Hz)	< 0.002%	Digital Section	
Intermodulation Distortion (60 Hz : 7k Hz, 4:1)	< 0.002%	Frequency Response	20 Hz - 20k Hz (0 ± 0.5 dB, Max)
Input Sensitivity / Impedance		Signal to Noise Ratio (IHF "A" weighted)	108 dB
Phono Input (MM)	2.5 mV / 47k ohms	Input Sensitivity/Impedance	0 dBFs / 75 ohms
Line Level Inputs (RCA)	150 mV / 100k ohms	Preamplifier Output Level	1.65 V (at - 20 dB)
Line Level Inputs (XLR)	250 mV / 100k ohms	Coaxial/Optical Digital Signals	SPDIF LPCM (up to 24-bit / 192k Hz)
Input Overload		PC-USB	USB Audio Class 1.0 (up to 24-bit / 96k Hz)
Phono Input	64 mV		USB Audio Class 2.0 (up to 32-bit / 384k Hz)* *Driver installation required
Line Level Inputs (RCA)	4 V		MQA and MQA Studio (up to 24-bit / 384k Hz)
Line Level Inputs (XLR)	5.5 V		Roon Tested
Output Level		Power Requirements	
Line Level (RCA)	1 V	Europe	230 V, 50 Hz
Balance (XLR)	2 V	USA	120 V, 60 Hz
Frequency Response		Power Consumption	45 watts
Phono Input	20 Hz-20k Hz (+0.3 dB, -0.2 dB)	Standby Power Consumption	< 0.5 watts
Line Level Inputs (RCA)	10 Hz-100k Hz (+0 dB, -0.1 dB)	BTU	78 BTU/h
Line Level Inputs (XLR)	10 Hz-100k Hz (+0 dB, -0.1 dB)	Dimensions (W x H x D)	431 x 144 x 348 mm 17 x 5 11/16 x 13 7/9 in
Tone Controls		Front Panel Height	3U / 132.6mm / 5 1/4 in
Bass	±10 dB at 100 Hz	Weight (net)	10.1 kg, 22.27 lbs.
Treble	±10 dB at 10k Hz	Finish	Silver and Black
Signal to Noise Ratio (IHF "A" weighted)			
Phono Input	80 dB		
Line Level Inputs (RCA)	117 dB		
Line Level Inputs (XLR)	115 dB		
Channel Separation			
Phono Input	> 85 dB		
Line Level Inputs (RCA)	> 85 dB		
Line Level Inputs (XLR)	> 75 dB		

All specifications are accurate at the time of printing.
Rotel reserves the right to make improvements without notice.

www.rotel.com

MQA and the Sound Wave Device are registered trade marks of MQA Limited. © 2016
Being Roon Tested means that Rotel and Roon have collaborated to ensure you
have the best experience using Roon software and the Rotel equipment together, so
you can just enjoy the music.