



Description

This high power two-channel amplifier can be used with the RMB-1575 to expand your theater system into a 7.1 system, or it can stand alone as a reference amplifier for a two-channel hi fi system. Either way, it has the same performance characteristics, sound quality, and custom installation options as the five-channel RMB-1575.

**Note – all Rotel 15 series components may be rack mounted and remotely controlled via RS-232, IR, or 12 volt (depending on model) for complete stealth operation.*

Specifications

Power Output all channels driven	250 watts x 2ch (20-20 kHz, 0.03% THD, 8 ohms) 500 watts x 2ch (20-20 kHz, 0.03% THD, 4 ohms)	Frequency Response	10 - 80 kHz (+/-3dB)
IM Distortion	< 0.03%	S/N Ratio (IHF A)	109 dB
Damping Factor (8 ohms)	400	Power Consumption	280 Watts
Gain	27.1 dB	Dimensions (W x H x D)	431x 99 x 339 mm (17 x 3 7/8 x 12 6/8 in)
Input Sens. / Impedance	1.5 V / 8.3 k ohms	Weight	7.8 kg (17.2 lbs)

www.rotel.com

The Rotel Co. Ltd.
10-10 Shinsen-Cho
Shibuya-Ku,
Tokyo 150, Japan

Rotel of America
54 Concord St.
N. Reading, MA 01864
USA
T +1 978 664 3820
F +1 978 664 4109

Rotel Europe
Dale Road
Worthing
West Sussex BN11 2BH, UK
T +44 (0) 1903 221 763
F +44 (0) 1903 221 525