

MICHI

X5

STEREO INTEGRATED AMPLIFIER



2 x 600 Watts of robust power



Class AB amplifier design



Texas Instruments premium 32-bit/768kHz Digital to Analog Converter



Bluetooth with apt-X and AAC



Supports MQA



Certified Roon Tested

The Michi X5 Integrated Amplifier is Performance Redefined delivering an astounding 600 Watts of Class AB power into 4 ohm speakers under even extreme loading conditions. The X5 is replete with inputs ensuring support of all popular audio sources including Analog, Digital, XLR, PC-USB with MQA rendering, apt-X Bluetooth, and selectable Moving Magnet or Moving Coil Phono Stage.

The acoustic eminence of the X5 is achieved utilizing a perfect balance of innovation and critical engineering of every circuit, signal path and audio component ensuring the exquisite industrial design is surpassed only by breathtaking performance.

Musical expression of the X5 is evidenced by the exceptional control of near limitless bass energy and essential clarity of the midrange and high frequencies. The X5 delivers true-to-life audio reproduction ensuring meticulous accuracy of the musical timing with exacting spatial positioning be it a solo artist or full orchestral symphony.

The X5 oversized, in-house manufactured toroidal transformer feeds 88,000uF of high efficiency bulk storage smoothing capacitors with isolated power supply feeds to all acoustically sensitive circuits eliminating unwanted noise or distortion further refining the audio.

A front panel high-resolution graphic display is configurable to show operating status, 12 band Graphic EQ or Peak Power Meter. Front panel controls and included Michi remote control assure easy operation and configuration.

Dual sets of Rhodium plated custom Michi speaker binding posts allow effortless connection to loudspeakers including bi-wire installations. RS232 and Ethernet connections allow simple integration with control systems.

Welcome to Michi. Acoustic Elevation, Sonic Evolution, Visual Perfection.

MICHI

X5

STEREO INTEGRATED AMPLIFIER



SPECIFICATIONS

Maximum Power Output	600 watts/channel (4 ohms)	Digital Section	
Continuous Power Output	350 watts/channel (8 ohms)	Frequency Response	20 Hz - 20k Hz (0 ± 0.4 dB)
Total Harmonic Distortion	< 0.009%	Signal to Noise Ratio (IHF "A" weighted)	102 dB
Intermodulation Distortion (60 Hz : 7 kHz, 4:1)	< 0.03%	Input Sensitivity/Impedance	0 dBFs / 75 ohms
Frequency Response		Preamplifier Output Level	1.2 V (at -20 dB Volume Position)
Phono Input	20 Hz-20k Hz (+0 dB, -0.2 dB)	Digital to Analog Converter	Texas Instruments PCM5242
Line Level Inputs	10 Hz-100k Hz (+0 dB, -0.6 dB)		32-Bit / 768kHz
Damping Factor (20 Hz - 20kHz, 8 ohms)	350	Coaxial/Optical Digital Signals	SPDIF LPCM (up to 192kHz 24 bit)
Input Sensitivity / Impedance		PC-USB	USB Audio Class 1.0 (up to 96kHz 24-bit) USB Audio Class 2.0 (up to 384kHz 32-bit)* *Driver installation required
Phono Input (MM)	5.7 mV / 47k ohms		MQA, DSD and DoP support
Phono Input (MC)	570 uV / 100 ohms		Roon Tested
Line Level Inputs (RCA)	380 mV / 100k ohms	Power Requirements	
Line Level Inputs (XLR)	580 mV / 100k ohms	Europe	230 V, 50 Hz
Input Overload		USA	120 V, 60 Hz
Phono Input (MM)	197 mV	Power Consumption	850 watts
Phono Input (MC)	19 mV	Standby Power Consumption	
Line Level Inputs (RCA)	12.5 V	Normal	< 0.5 watts
Line Level Inputs (XLR)	12.5 V	Network Wakeup	< 2 watts
Preamplifier Output Level / Impedance	1 V / 470 ohms	BTU (4 ohms, 1/8 power)	2194 BTU/h
Tone Controls		Dimensions (W x H x D)	485 x 195 x 452 mm 19" x 7 5/8" x 17 3/4"
Bass	±10 dB at 100 Hz	Front Panel Height	177 mm / 7"
Treble	±10 dB at 10k Hz	Weight (net)	43.8 kg, 96.56 lb
Signal to Noise Ratio (IHF "A" weighted)		Finish	Black
Phono Input (MM/MC)	80 dB		
Line Level Inputs	102 dB		
Channel Separation			
Phono Input (MM)	> 65 dB		
Line Level Inputs	> 65 dB		

All specifications are accurate at the time of printing.
Michi reserves the right to make improvements without notice.